



XP5250EH

DUAL FUEL PORTABLE GENERATOR
5,250 STARTING WATTS • 4,200 RUNNING WATTS






XP5250EH

DUAL FUEL PORTABLE GENERATOR

FEATURES



OUTLETS



X2
120V 20A
GFCI Outlet



X1
120V 30A
RV Outlet



**DOUBLE THE
120V AMPERAGE**

SPECS

Watts (Gasoline)	5,250 (peak) • 4,200 (running)
Watts (Propane)	5,000 (peak) • 4,000 (running)
Engine	OHV 224cc
Amperage	35.00A
Voltage	120VAC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	8 hrs
Runtime (Propane) at 50% Load	7 hrs